



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

Outbound (CX Contact) Private Edition Guide

Dial Manager metrics and alerts

Contents

- [1 Metrics](#)
- [2 Alerts](#)

Find the metrics DM exposes and the alerts defined for DM.

Related documentation:

-

Service	CRD or annotations?	Port	Endpoint/Selector	Metrics update interval
Dial Manager	ServiceMonitor	3109	/metrics	15 seconds

See details about:

- Dial Manager metrics
- Dial Manager alerts

Metrics

Metric and description	Metric details	Indicator of
cxc_dm_healthy_instance Healthy instance.	Unit: Type: Gauge Label: n/a Sample value: 4.2	
cxc_dm_processed_batches_total Total processed batches.	Unit: Type: Counter Label: ""media', 'ccid', 'tenant_name"" Sample value: 42	
cxc_dm_processed_messages_total Total processed messages.	Unit: Type: Counter Label: ""media', 'ccid', 'tenant_name"" Sample value: 42	
cxc_dm_opt_out_messages_total Total opt out messages.	Unit: Type: Counter Label: ""media', 'ccid', 'tenant_name"" Sample value: 42	
cxc_dm_failed_processed_messages_total Total failed messages.	Unit: Type: Counter Label: ""media', 'ccid', 'tenant_name"" Sample value: 42	

Metric and description	Metric details	Indicator of
cxc_dm_batch_size Batch size histogram.	Unit: Type: Histogram Label: "'media', 'ccid', 'tenant_name'" Sample value: [1, 2, 3]	
cxc_dm_process_message_duration_seconds Processing message duration histogram.	Unit: Type: Histogram Label: "'media', 'ccid', 'tenant_name'" Sample value: [1, 2, 3]	
cxc_dm_delivery_buffer_size Delivery buffer size.	Unit: Type: Gauge Label: 'media' Sample value: 4.2	
cxc_dm_test_messages_total Total test messages.	Unit: Type: Counter Label: "'media', 'ccid', 'tenant_name'" Sample value: 42	
cxc_dm_failed_test_messages_total Total failed test messages.	Unit: Type: Counter Label: "'media', 'ccid', 'tenant_name'" Sample value: 42	
cxc_dm_nexus_service_status The current status of the connection to the Nexus service.	Unit: Type: Gauge Label: "'ccid', 'tenant_name'" Sample value: 4.2	
cxc_dm_request_count Total requests made to Nexus via websocket.	Unit: Type: Counter Label: "'media', 'ccid', 'tenant_name', 'code'" Sample value: 42	
cxc_dm_request_latencies_ms Request latencies histogram by tenant, in milliseconds.	Unit: Type: Histogram Label: Sample value: [1, 2, 3]	
cxc_dm_request_out_count Total out requests by verb, destination, and code.	Unit: Type: Counter Label: "'method', 'destination', 'code'" Sample value: 42	
cxc_dm_request_out_latencies_ms Out Request latencies histogram by verb, destination, and code, in milliseconds.	Unit: Type: Histogram Label: Sample value: [1, 2, 3]	
cxc_dm_elasticsearch_service_latencies_ms	Unit:	

Metric and description	Metric details	Indicator of
Elasticsearch Request latencies histogram by verb, destination, and code, in milliseconds.	Type: Histogram Label: "'method', 'destination', 'code'" Sample value: [1, 2, 3]	

Alerts

The following alerts are defined for Dial Manager.

Alert	Severity	Description	Based on	Threshold
CXC-DM-LatencyHigh	HIGH	Triggered when the latency for dial manager is above the defined threshold.		5000ms for 5m
CXC-CPUUsage	HIGH	Triggered when the CPU utilization of a pod is beyond the threshold		300% for 5m
CXC-MemoryUsage	HIGH	Triggered when the memory utilization of a pod is beyond the threshold.		70% for 5m
CXC-PodNotReadyCount	HIGH	Triggered when the number of pods ready for a CX Contact deployment is less than or equal to the threshold.		1 for 5m
CXC-PodRestartsCount	HIGH	Triggered when the restart count for a pod is beyond the threshold.		1 for 5m
CXC-MemoryUsagePD	HIGH	Triggered when the memory usage of a pod is above the critical threshold.		90% for 5m
CXC-PodRestartsCountPD	HIGH	Triggered when the restart count is beyond the critical threshold.		5 for 5m
CXC-PodsNotReadyPD	HIGH	Triggered when there are no pods ready for CX Contact deployment.		0 for 1m