

GENESYS[®]

This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

Gplus Adapter for ServiceNow Agent's Guide

Get started with Gplus Adapter

7/15/2025

Contents

- 1 Log in
- 2 Gplus Adapter main view
- 3 Log out
- 4 Supported channels
- 5 Relevant links

Here is an introduction to the Gplus Adapter for ServiceNow.

The Gplus Adapter for ServiceNow provides integrated management of communication channels within the ServiceNow CRM.

Link to video

Watch the following video if you are using the ServiceNow Agent Workspace.

Link to video

Log in

Using ServiceNow **OpenFrame**, Gplus Adapter is loaded and displayed during the ServiceNow login sequence. Log in to your ServiceNow account; then continue logging into the Genesys Adapter.

servicenow. Service Management		Gplus-Adapter X	🏐 System Administrator 🔹 🕓 Q 🗗 🕐 🚳
Titter navigator	+ System Administration +		0 ©
E ★ 🕓	Make your life easier, create a dashboard!		×
Homepage	Did you know you can create a dashboard version of this homepage? Dashboards are like hom tabs. Flexible sharing lets any user view and collaborate on dashboards with you!		sily add, move, and resize widgets. You can also add multiple
Business Applications	Don't ask me again Bernind me later	S GENESYS	Create dashboard version
Dashboards		Workspace	
Service Catalog			
Knowledge	Guided Setup Guided Setup tools to help you set up ServiceNow	Username	Business Logic Manage workflow and behavior of applications
Visual Task Boards	•**	Tenant name	r
Connect Chat	Create and Deploy	Remember me	Diagnostics
Incidents	Create and Deploy Create, modify and deploy applications to your instances	Next	Performance, development and debugging tools
Watched Incidents			
My Requests	Email Customize behavior of inbound and outbound email		Integration
Requested Items	Customize behavior of inbound and outbound email		K
Watched Requested Items			
My Connected Apps	Reporting and Analytics Create visual representations of your data		User Interface Control the look and feel of applications
My Profile		3	
My Tagged Documents			ď
My Tags			0
0			

If you are prompted to log in, enter your Genesys username (like an email address) and password and click **Log in**. If you have logged in before, your username should already be entered. If you have logged into the Adapter previously, the login page automatically inputs your last known place. More often you can accept the last known place, before clicking **Log in**.

Gplus Adapter main view

After you log in, the main view is displayed. From this view, you can **change your status** and make calls.

The Genesys Gplus Adapter displays your name on the upper right. Click your name to check information about yourself: your current status, the duration of your status, your particular phone place, and your login time.

Servicenow. Service Management		🖬 GP-Adapter-Set 🕘 System Administrator 🔹 📞 🔍 🗗 🕐 🗔
Tilter navigator	E Incidents [Self Service view] New Search Number V Search	~
e \star ()	▼ All > Caller = +33298025555 > Active = true (2): Q ■ Number ▼ ■ Opened	Genesys Adapter
Self-Service		O 🕺 O John Smith 🖕
Homepage	No records to	
Business Applications		Not Ready (00:01)
Dashboards		Logged in since 10:08 AM Using Place_JohnSmith
Service Catalog		voice Not Ready
Knowledge		
Help the Help Desk		
Visual Task Boards		
Connect Chat		
Incidents		
Watched Incidents		
My Requests		
Requested Items		
Watched Requested Items		

When you first log in, notice that your agent status is set for you — for instance, it could be **Not Ready**. Click your name to change your status; you can choose among:

- Ready
- Not Ready with or without a reason
- Do not disturb
- · Log Off.

Log off enables you to log out of Genesys but remain connected to the Adapter.

Servicenow Service Management	GP-Adapter-S	er-Sei 🛊 🅘 System Ad	iministrator • 📞 🔍 🗗 💮 🔅
Filter navigator	E Incidents (Self Service view) New Search Number V Search		~
E ▲ ①	✓ All>Caller=+33298025555>Active = true (2) Q ■ Number ▼	Genesys Adapter	Sohn Smith A
Homepage	No records to display	0 *	🖉 John Smith A
Business Applications Dashboards			 Not Ready Not Ready - Break
Service Catalog Knowledge			 Not Ready - Lunch After Call Work
Help the Help Desk			After Call Work - Jelly Bean After Call Work - Kit Kat
Visual Task Boards Connect Chat			 Do Not Disturb Log Off
Incidents			
Watched Incidents My Requests			
Requested Items Watched Requested Items			

The default state you find at your first login is determined by your system administrator either for the whole contact center/agent group or specifically for you. If your status is not already set to **Ready**, change it in order to receive inbound calls.

Log out

To log off all channels and sign out of Gplus Adapter for ServiceNow, click the menu button and then select **Exit**.

		🗂 📴 GP-Adapter-Set i 📵 System Administrator 🔹 🌜 🔍 🗗 🕐 🚳
Filter navigator	E Incidents [Self Service view] New Search Number	~
⊡ ★ ©	XII>Caller = +33298025555 > Active = true	Genesys Adapter X
Self-Service	O ■ Number ▼ ■ Opened	oo 🟦 🚥 📀 John Smith 🗸
Homepage	No records to	o display
Business Applications		
Dashboards		

The Adapter returns you to the login page, you must enter your credentials to log in again. When you log out, ensure your interactions are completed before logging out from ServiceNow and closing your browser window.

You can't sign out if there are any active calls. If you try, an error message is displayed. You must click **OK** before you can continue working with the Adapter.

Supported channels

The Gplus Adapter currently supports the **voice channel** and the **workitem channel**. It provides you with controls and features that enable you to handle voice interactions with contacts or internal targets (like other agents).

Voice user experience:

Once you are in an active call — because you called someone, or someone called you — the main view changes to the **active call toolbar**. It is visible at the top of the Adapter and displays all applicable call controls and a timer for the active call.

Servicenow. Service Management				GP-A	Adapte	📫 🌒 System Administrator 🔹 📞	< ୮୦ ଡ଼ 🏟
Filter navigator	$\leq \equiv \frac{\text{Incident}}{\text{INC0010111}}$				1	√ ★ ••• Follow ▼ Update	Resolve Delete
e * 0	Number	INC0010111		Cont	tact	Genesys Adapter	×
Self-Service	* Caller	+332980255555	Q,	•C •			John Smith Y
Homepage Business Applications	Category	Inquiry / Help	٥		Irr(∞ ୯୯୯Ⅲ-୯- ೭,-&-	2 ~
Dashboards	Subcategory	None	0		Urg	ase Information	+ ~
Service Catalog	Service		Q		Pri	rigin Inbound call to +332980255555	
Knowledge	Configuration item		Q	Assignmer	int g	riority 8	
Help the Help Desk				Ass	sign	all Type Inbound egment Gold	
Visual Task Boards	* Short description	Call Inbound from +332980255555 - Con	nection	ild: 1	-1	+332980255555 🕲 Connected	
Connect Chat				Related Search Results >		ispositions	
Incidents						Quick Search	
Watched Incidents	Skills	&				Accepted	
My Requests	Notes Related Records	Resolution Information				Rejected Transfered	
Requested Items	Watch list	8 2		Work n	note		
Watched Requested Items	Work notes	Work notes				+332980255555	

Call controls include:

Icon	Function	Description
C.	Release Call	Ends the call.
C	Hold Call	Places the call on hold. After the call is holding, the Retrieve button is displayed.
	Direct Transfer	Redirects the call to another contact you select using Team Communicator.
2	Consultative Transfer	Starts a consultation with another contact before transferring the call to that contact.

lcon	Function	Description
<u>*</u>	Conference	Starts a voice conference instantly with the current caller and an additional contact that you select using Team Communicator.

In case of multiple interactions at the same time, you can click the **phone icon** at the bottom of the Adapter to verify the status of each call. A green bar indicates an active call; inactive calls are indicated by a red bar.

Servicenow. Service Management	🖾 GP-Adapter-Sei 🗧 🎒 System Administrator 🔹 📞 🔍 🗗	?
Filter navigator	< ≡ Incident INCC0101111	e Delete
⊡ ★ ©	Genesys Adapter Number INC0010111 Contact	×
Self-Service	* Caller +332980255555 Q, +C %, ()	h Y
Homepage	Category Inquiry/Help e Irr 00:49	
Business Applications Dashboards	Subcategory None Case Information +	
Service Catalog	Service Q, Et Origin Inbound call to +332980255555	
Knowledge	Configuration item Q. Assignment g Priority 8 / Call Type Inbound /	
Help the Help Desk	Kosign Segment Gold Segment Gold	
Visual Task Boards	: +33298025555	
Connect Chat	Related Search Results > Dispositions	
Incidents Watched Incidents	Skills & Accepted	
My Requests	Notes Related Records Resolution Information Rejected Transfered	
Requested Items	Watch list 🙆 2 Work note	
Watched Requested Items	Work notes Work notes +33298025003	

If you wish to learn how to work with the Adapter, continue to see the page How to manage inbound calls.

WorkItem interaction user experience:

When you handle a workitem the interaction window is displayed in the GPlus adapter:



Workitem controls include:

Icon	Function	Description
■ ↓	Save to Workbin	Move the workitem back to workbin
2	Direct Transfer	Redirects the call to another contact you select using Team Communicator.
<u>.</u>	Consultative Transfer	Starts a consultation with another contact before transferring the call to that contact.
	Mark Done	Mark Done the workitem interaction

in case of multiple interactions at the same time, you can click the WorkItem Icon at the bottom of the Adapter to verify the status of each WorkItem Interaction



Relevant links

- How to manage inbound calls
- How to make outbound calls
- How to handle a workitem
- How to handle screen pops in ServiceNow